

MILITEC LTD

C9200M TARGET CONTROL HANDSET



The C9200M Range controller can be supplied in a range of languages.

It is an easy to use radio handset, which enables the user to:-

- i) Manually control individual targets, groups of targets and movers.
- ii) Provide a simple timer facility to program and run Face/Edge/Repeat sequences.
- iii) Allow shoot programs configured on a PC, using the Militec PC-Shoot software, to operate target bases independently or in groups, with different time exposures and hit reactions.
- iv) Controller to PC download lead USB to Mini USB type B

Hit results can be viewed on the screen and uploaded to the PC if required.



GENERAL FEATURES

| | |
|-------------------------------------|--|
| Weight | 500 grams, including batteries and leather case |
| Size | 235mm x 120mm x 60mm. (L x W x H) |
| Keypad operation | 4 x 7 membrane keypad |
| Display | Graphic display with contrast control |
| Power | 4 No. 1.2V NiMH, re-charged via charge socket |
| Radio transceiver | 400-460MHz 100mW 8 separate channels with 50KHz spacing |
| Frequency agility | Target identification address number and/or radio channel can be changed from the handset |
| Manual control | Individual or Group or All target units |
| Local programming On the handset | Face/ Edge timing 1 to 999 secs Sequence repeat 1 to 999 times Internally stored |
| PC programming | PC Shoot software Shoot programs uploaded via USB link Program length, 1000 seconds not including pauses |
| Operational capabilities | 250 target units Operational distance up to 1000 metres depending on terrain Displays hit results for each target together with the time taken for the first bullet to hit the target after exposure Individual hit sensor sensitivity adjustment Battery status interrogation Targets can be switched off remotely |
| Target hit reaction settings | Bounce Back , target turns away after 1 - 9 hits and return to face after 1 sec Turn When Hit , target turns away when hit 1 - 9 times and stays away Hold target will not react to hits |
| Night light settings | a) Lamp ON for 1 to 4 seconds on Face (selectable in 1 sec steps.), with 0.5 sec. flash when hit b) Lamp On and stays ON until the target turns away |
| IP Protection | IP65 |
| Compatible Equipment | M2100M, M2200MF, M3450M, M3200M, M3600M, M3720M, M5150Mv2, M4500M, M4500MF |