

# MILITEC LTD

## C9200M TARGET CONTROL HANDSET



The C9200M Range controller can be supplied in any language, it is an easy to use radio handset, which enables the user to:-

- i) manually control individual targets, groups of targets and movers.
- ii) provide a simple timer facility to program and run Face/Edge/Repeat sequences.
- iii) allow shoot programs configured on a PC, using the Militec PC-Shoot or MATRIX configuration software, to operate target bases independently or in groups, with different time exposures and hit reactions.
- iv) Controller to PC download lead USB to Mini USB type B

Hit results can be viewed on the screen and uploaded to the PC if required.



## GENERAL FEATURES

Weight	500 grams, including batteries and leather case
Size	235mm x 120mm x 60mm. (L x W x H)
Keypad operation	4 x 7 membrane keypad
Display	Graphic display with contrast control
Power	4 No. 1.2V NiMH, re-charged via charge socket
Radio transceiver	400-460MHz 100mW 8 separate channels with 50KHz spacing
Frequency agility	Target identification address number and/or radio channel can be changed from the handset
Manual control	Individual or Group or All target units
Local programming On the handset	Face/ Edge timing 1 to 999 secs Sequence repeat 1 to 999 times Internally stored
PC programming	PC Shoot or MATRIX trainer software Shoot programs uploaded via USB link Program length, 1000 seconds not including pauses
Operational capabilities	250 target units Operational distance up to 1000 metres depending on terrain Displays hit results for each target together with the time taken for the first bullet to hit the target after exposure Individual hit sensor sensitivity adjustment Battery status interrogation Targets can be switched off remotely
Target hit reaction settings	<b>Bounce Back</b> , target turns away after 1 - 9 hits and return to face after 1 sec <b>Turn When Hit</b> , target turns away when hit 1 - 9 times and stays away <b>Hold</b> target will not react to hits
Night light settings	a) Lamp <b>ON</b> for 1 to 4 seconds on Face (selectable in 1 sec steps.), with 0.5 sec. flash when hit b) Lamp <b>On</b> and stays <b>ON</b> until the target turns away
IP Protection	IP67

**The C9200M handset controller is fully compatible with all Militec target equipment**